

EP 2200-T

010-022-10



Product Description





Multilink is your source for a complete array of products for the DOT/ITS market. Multilink designs and manufactures an extensive product line of high-quality aluminum and stainless steel traffic control cabinets, Uninterruptable Power Supplies and LED Illuminated Street Signs and Lane Use Control and Blank –Out Signs'

Specifications

Parameter	Specification
Dimensions:	5.24 x 17 x 10
Output Power:	1,500W / 2kVA
Weight:	20 Kg (44 lbs.)
Audible Noise:	<60dB
Efficiency:	98% (resistive)
Operating Temperature w/ batteries:	-35°C to +74°C
Mounting:	Vertical or Horizontal 19" or 23"
Storage Temperature Range:	-50°C - 80°C
Frequency:	60Hz
Voltage Range:	90V - 150V

Buck/Boost Range:	Programmable $\pm 20\%$
Waveform:	True Sine Wave
Nominal Voltage:	2,000VA
Voltage Regulation:	$\pm 2\%$ Max.
Typical Output Voltage THD:	<3%
Typical Transfer Time:	<5ms
Safety Standards:	UL1778:2014 Ed. 5 CSA 22.2#107.3:2014 Ed.3 RoHS Compliant NEMA TS-2-2016v03.07

Accessories

[Accessories]		
Products	Description	Stock ID
	3 Battery, 36V External Battery Balance Manager (BBM Plus)	018-008-20
	4 Battery, 48V External Battery Balance Manager (BBM Plus)	018-009-20
	48V Battery Harness	870-230-10
	538-531-10	538-531-10

Contact Us

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: hquinones@gomultilink.com

Multilink®

Simply More...



Multilink Inc.
 580 Ternes Ln
 Elyria, OH 44035
 Tel: (440) 366-6966
 Fax: (440) 366-6802



facebook.com/GoMultilink1



twitter.com/GoMultilink



youtube.com/GoMultilink

© Multilink Inc. 2020 • All Rights Reserved

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: hquinones@gomultilink.com

Contact Us